

1. 패스워드 Recovery 절차

▶ 대상제품.

. L2 Switch : E5708C, E5708R, E5724R

▶ STEP 1.

- 콘솔 연결 및 장비를 리부팅하여, 부트모드로 진입 (부팅직후, CTRL+C 입력)

```
== 종료 ==
Hit Ctrl+C key to stop autoboot: 2
ubiQuoss#
```

▶ STEP 2.

- 부트모드 프롬프트에서 패스워드를 초기화/저장 실행

```
ubiQuoss# setenv epasswd yes
ubiQuoss# saveenv
Saving Environment to SPI Flash...
Erasing SPI flash...100%
Writing to SPI flash...II: Writting 65536 bytes to 00080000... 100%
done
ubiQuoss# run bootflash
DONE !!!
```

▶ STEP 3.

- 부팅완료 및 Default Password 로 장비 접속여부 확인

```
Switch login: root
Password : premier
Switch> enable
Switch#
```

[첨부] Config 초기화 설정 or Password 변경.

- Config 초기화 설정

```
Switch> enable
Switch# erase startup-config
```

```
Warning: start.cfg is the next booting config file
Do you want to erase it? [yes/no] yes
Next boot config file was erased from flash filesystem!!
```

- Password 변경

```
Switch> enable
Switch# configure terminal
Switch(config)# username root password [변경 Password 입력]
Switch(config)# end
Switch# copy running-config startup-config
Overwrite 'start.cfg_bak'? [yes/no] yes
```